

Product datasheet

Specifications



1 Gang 250VA Fan Speed Controller

KB31RF250

Main

Range	Vivace
Device Short Name	KB31
Product Or Component Type	Speed controller
Device Presentation	Complete mechanism
Colour Tint	White

Complementary

Power Range	Motor: 250 VA
[Ue] Rated Operational Voltage	220...240 V AC
Network Frequency	50 Hz
Number Of Gangs	1 gang
Connections - Terminals	Pillar terminals
Terminal Identifier	L Load
Tightening Torque	0.4 N.m
Clamping Connection Capacity	1.5 mm ²
Contacts Material	Brass and phosphor bronze
Material	Polycarbonate: grid plate Polycarbonate: surround Nylon: base
Device Mounting	Flush
Mounting Support	Wall mounted
Fixing Mode	By screw M3.5
Fixing Center	60.3 mm
Width	87 mm
Height	87 mm
Projecting Depth	8 mm
Embedding Depth	35 mm

Environment

Ambient Air Temperature For Operation	-5...40 °C
Relative Humidity	0...95 %
Environmental Characteristic	Indoor use

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Weight	130.875 g

Contractual warranty

Warranty	18 months
----------	-----------

Sustainability

Green Premium™ label is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product's sustainability >](#)



Transparency RoHS/REACH

Well-being performance

Mercury Free

RoHS Exemption Information Yes

Certifications & Standards

Reach Regulation [REACH Declaration](#)

Eu RoHS Directive Compliant with Exemptions

China RoHS Regulation [China RoHS declaration](#)
Product out of China RoHS scope. Substance declaration for your information

Environmental Disclosure [Product Environmental Profile](#)

Circularity Profile [End of Life Information](#)